

QRM-01C Single Zone paging Condenser Microphone

Optional single zone paging microphone with push-to-talk switch and XLR output.

The QRM-01C condenser gooseneck microphone delivers high fidelity performance for a variety of applications. Ideal for restaurants, retail stores, medical/dental offices, schools, factories, warehouses, boardrooms, educational and more, the QRM-01C offers a wide dynamic range and smooth frequency response for high-quality audio reproduction. Features includes push-to-talk switch, removable windscreen, battery operation, and red indicator light to show when the mic is active



KEY SPECIFICATIONS

- Push-to-talk switch
- XLR microphone input for the included gooseneck microphone
- XLR output for easy connection to any equipment.
- Red indicator light to show when the mic is Active.
- 48V phantom power required.
- If no phantom power is available, it can be powered by 2x AAA batteries.
- Removable windscreen



Commercial audio solutions for every application

Specifications

Model #	QRM-01C
Microphone Type	Condenser Microphone
Frequency Response	40Hz~16kHz
Sensitivity	-40dB ±2dB
Required Phantom Power	3V DC (battery) or 48V Phantom
Output Impedance	75Ω
Required for Battery operation	2x AAA (Not Included)
Weight (Net)	1.10 lbs. (0.5 kg)
Carton Dimensions (Width/Height/Depth)	7.9(W) x 2.4(H) x 4.7(D) inches 200(W) x 60(H) x 120(D) mm
UPC Code	694970008601