

PS-65B / PS-65W 2-Way Pendant Speaker

6.5" 2-Way Pendant Speaker - 125W (8 Ohms), 60W (70V).



SPECIFICATIONS

- 70V / 100V / 8 Ohms selectable
- 70.7V Taps: 3.75W, 7.5W, 15W, 30W, 60W
- 100V taps: 7.5W, 15W, 30W, 60W
- Sensitivity: 88.5 dB (1W/1m)
- Power: 100W Program (8Ω)
- Frequency Response : 50 – 20 KHz
- Crossover Frequency: 2.5 kHz
- Coverage Angle: 100°
- Diameter: 9.92" (252mm)
- Height: 9.52" (241mm)
- Weight: 10 lb. (4.5kg)